

Dimmer Compatibility

For Gotham LED Luminaires

ALED, ALEDW, ALEDR, DLWLED, CLED, ECSR, ECSS,
4DR5, 6DR5, 4DS5, 6DS5

ALED, ALEDW, ALEDR, DLWLED, CLED, ECSR, ECSS		
COMPATIBLE 0-10V WALL-MOUNT DIMMERS		
MANUFACTURER	PART NO.	POWER BOOSTER AVAILABLE
Lutron	Diva® DDTV	
	Diva® DVSCTV	
	Nova T® NTFTV	
	Nova® NFTV	
Leviton	AWSMT-7DW	CN100 PE300
	AWSMG-7DW	
	AMRMG-7DW	
	Leviton Centura Fluorescent Control System	
	IllumaTech™ IP7 Series	
Synergy	ISD BC	RDMFC
	SLD LPCS	
	Digital Equinox (DEQ BC)	
Douglas Lighting Controls	WPC-5721	
Entertainment Technology	Tap Glide TG600FAM120 (120V)	
	Tap Glide Heatsink TGH1500FAM120 (120V)	
	Oasis OA2000FAMU	
Honeywell	EL7315A1019	EL7305A1010 (optional)
	EL7315A1009	
HUNT Dimming	Preset slide: PS-010-IV and PS-010-WH	
	Preset slide: PS-010-3W-IV and PS-010-3W-WH	
	Preset slide, controls FD-010: PS-IFC-010-IV and PS-IFC-010-WH-120/277V	
	Preset slide, controls FD-010: PS-IFC-010-3W-IV and PS-IFC-010-3W-WH-120/277V	
	Remote mounted unit: FD-010	
Lehigh Electronic Products	Solitaire	PBX
PDM Electrical Products	WPC-5721	
Starfield Controls	TR61 with DALI interface port	RT03 DALI.net Router
The Watt Stopper, Inc.	LS-4 used with LCD-101 and LCD-103	

Dimmer Compatibility for Gotham LED Luminaires

4DR5, 6DR5, 4DS5, 6DS5		
COMPATIBLE ELECTRONIC LOW-VOLTAGE WALL-MOUNT DIMMERS: Trailing Edge Dimmers (Reverse-Phase Dimmers)		
MANUFACTURER	PART NO.	POWER BOOSTER AVAILABLE
Lutron	Diva® DVELV-300P 300-watt single pole	N/A
	Diva® DVELV-303P 300-watt single pole	
	Nova T® NELV-300 300-watt single pole	
	Nova T® NELV-450 450-watt single pole	
	Nova T® NELV-600 600-watt single pole	
	Skylark® SELV-300P 300-watt single pole	
	Skylark® SELV-303P 300-watt 3-way	
	Maestro® MAELV-600 600-watt single pole	
	Interface® ELVI-1000 1000-watt single pole	
Leviton	Sureslide® R02-06615-P0W 600-watt single pole	N/A
	Sureslide® R02-06615-P0W 600-watt 3-way	
	Vizia® VZE06-1LZ 600-watt single pole	
	Vizia® VZE06-1LZ 600-watt 3-way	
	Acenti® ATE04-1LW, ATE04-1LA	
	Acenti® ATE06-1LW, ATE06-1LA	
	IllumaTech™ IPE04	